

Output voltage	Number of power modules											
	1	2	3	4	5	6	7	8	9	10	11	12
0-12V	300A	600A	1200A	1800A	2400A	3000A	3600A	4200A	4800A	5400A	6000A	
0-15V	250A	500A	1000A	1500A	2000A	2500A	3000A	3500A	4000A	4500A	5000A	
0-20V	200A	400A	800A	1200A	1600A	2000A	2400A	2800A	3200A	3600A	4000A	
0-24V	–	300A	600A	900A	1200A	1500A	1800A	2100A	2400A	2700A	3000A	
0-30V	–	250A	500A	750A	1000A	1250A	1500A	1750A	2000A	2250A	2500A	
0-36V	–	–	–	600A	–	–	1200A	–	–	1800A	–	
0-40V	–	200A	400A	600A	800A	1000A	1200A	1400A	1600A	1800A	2000A	
0-45V	–	–	–	500A	–	–	1000A	–	–	1500A	–	
0-48V	–	–	300A	–	600A	–	900A	–	1200A	–	1500A	
0-60V	–	–	250A	400A	500A	600A	750A/ 800A	–	1000A	1200A	1250A	
0-72V	–	–	–	300A	–	–	600A	–	–	900A	–	
0-75V	–	–	–	–	–	500A	–	–	–	–	1000A	
0-80V	–	–	200A	–	400A	–	600A	–	800A	–	1000A	
0-84V	–	–	–	–	–	–	–	600A	–	–	–	
0-90V	–	–	–	250A	–	–	500A	–	–	750A	–	
0-96V	–	–	–	–	300A	–	–	–	600A	–	–	
0-100V	–	–	–	–	–	400A	–	–	–	–	800A	
0-105V	–	–	–	–	–	–	–	500A	–	–	–	
0-108V	–	–	–	–	–	–	–	–	–	600A	–	
0-120V	–	–	–	200A	250A	300A	400A	–	500A	600A	600A	
Height*	450 mm	450 mm	590 mm	730 mm	870 mm	1010 mm	1150 mm	1290 mm	1570 mm	1710 mm	1850 mm	
Weight*	42 kg	49 kg	76 kg	102 kg	133 kg	160 kg	188 kg	220 kg	251 kg	286 kg	315 kg	

** The red 'D' symbol means that the rectifier can have dual outputs with maximum current halved.